

How to add SIM and APN settings to SVD for CMS use

This guide will show you how to add SIM details and the CMS Server IP to your SVD.

Please have the SIM card inserted into the back of the SVD unit.

Using the remote control enter the menu – default password 6666



Select Network



LAN



A screenshot of a configuration menu titled "LAN". The menu contains several fields: "Net type" is a dropdown menu set to "LAN"; "DHCP" is a dropdown menu set to "OFF"; "Static IP" is a text box containing "192.168.002.246"; "Net mask" is a text box containing "255.255.255.000"; "Gateway" is a text box containing "192.168.002.100"; "DNS" is a text box containing "202.096.134.033"; "Sever IP" is a text box containing "cvideoview.com"; and "Sever port" is a text box containing "8101". At the bottom right, there are "OK" and "Cancel" buttons. A small yellow lightbulb icon is visible in the bottom left corner.

Change Net type to 3G/4G-WIFI



A screenshot of a configuration menu titled "LAN". The menu contains several fields: "Net type" is a dropdown menu set to "3G/4G-WIFI"; "DHCP" is a dropdown menu set to "ON"; "Static IP" is a text box containing "192.168.002.246"; "Net mask" is a text box containing "255.255.255.000"; "Gateway" is a text box containing "192.168.002.100"; "DNS" is a text box containing "202.096.134.033"; "Sever IP" is a text box containing "cvideoview.com"; and "Sever port" is a text box containing "8101". At the bottom right, there are "OK" and "Cancel" buttons. A small yellow lightbulb icon is visible in the bottom left corner.

You will now need to enter your hosting CMS server IP address; the default port is 8101.

You can also use a DNS name if you wish.

Once complete press OK.

In the previous menu select 3G/4G



Now you can enter your SIM ISP details.

Once complete press enter.

There is a separate document for the install process for the server software.